

Siemens (Furnas) Pumping Plant Panels

- **Siemens Brand (Furnas).**
- **NEMA sized contactors.**
- **ESP 2 overloads.**
- **NEMA 3R enclosure.**
- **Removable door.**
- **External reset button.**
- **Fused disconnect switch.**
- **H-O-A switch.**
- **Push to start button.**



Siemens ESP 2 Pumping Plant Panels (3 Phase)										
HP	Volts	Panel w/ Fuses Product Number	Panel Only Product Number	Fuse Clip Size (Amps)	Fuse Size Req. (Amps)	NEMA Size	O/L Setting Range (Amps)	Motor Amp Setting (Amps)	Coil Number	
1.5	230	FP30015	87DUD6LC	30	7	1	5.5-22	5.9	75D73070C	
2		FP30020			10			8.1		
3		FP30030			12			10.9		
5		FP30050			20			17.8		
7-1/2	230	FP30075	87DUE6LC	30	30	1	10-40	26.4		
10	230	FP30100	87EUE6LC	60	35	1-3/4	10-40	32.2		
15	230	FP30150	87FUF6LC	60	60	2	13-52	45.0		
20	230	FP30200	87GUG6PC	100	70	2-1/2	25-100	60.6		
25	230	FP30250	87HUG6LC	100	90	3	25-100	75.0		75D73251C
30		FP30300			100			90.4		
1-1/2	460	FP40015	87DUC6FC	30	10	1	2.5-10	3.0	75D73070C	
2		FP40020			10			4.1		
3		FP40030			10			5.5		
5		FP40050			10			8.9		
7-1/2	460	FP40075	87DUD6FC	30	15	1	5.5-22	12.3		
10		FP40100			20			16.1		
15	460	FP40150	87EUE6FC	30	30	1-3/4	10-40	23.7		
20	460	FP40200	87FUF6FC	60	35	2	13-52	30.3		
25		FP40250			45			37.5		
30	460	FP40300	87GUG6FC	60	50	2-1/2	13-52	45.2		
40	460	FP40400	87HUG6FC	100	70	3	25-100	49.6	75D73251C	
50		FP40500			90			61.6		
60	460	FP40600	87IUH6FC	200	110	3-1/2	50-200	91.0		
75		FP40750			125			107.0		
100	460	FP41000	87JUH6FC	200	175	4	50-200	144	75D70131C	
125	460	FP41250	87LPU6FH	400	225	5	55-250	189		
150		FP41500			250			221		
175		FP41750			300			250		
200		FP42000			350			250		